



# Cone Ring Coupling

Size	Power Ratings (Kw @ )						Nominal Torque (Nm)
	100 rpm	720 rpm	960 rpm	1440 rpm	2880 rpm	Max .rpm	
020							
030	0.16	8.4	11.1	16.7	33.4	4600	110
038	1.87	13.5	18.0	26.9	53.9	4400	175
042	2.84	20.4	27.3	40.9	81.8	4000	265
048	4.93	35.5	47.3	71.0	142.0	3400	465
058	7.54	54.3	72.4	108.6	217.2	3020	720
070	10.70	77.0	102.7	154.1	-	2700	1020
075	25.7	185.0	246.7	370.1	-	2300	2450
085	35.5	255.6	340.8	511.2	-	2090	3390
105	53	382	509	763	-	1760	5080
120	90	648	864	1296	-	1570	8474
135	122	878	1171	-	-	1390	11520
150	159	1145	1526	-	-	1280	15140

## Selection Procedure

1. From the service factors table (below) determine the service factor
2. Calculate the Design Power by multiplying the Absorbed Power of the driven machine by the Service Factor.
3. Determine the size of coupling required by matching the design power to a power rating that matches or exceeds the Design Power.

The Pin Half is normally mounted on the drive shaft.

Duty	Electric Motors
Uniform	1.0
Light	1.5
Moderate	2.0
Heavy	2.5
Severe	3.0